



Issued Date

Issued By

6/20/2025

dschoeck

Transmit #

Issued Rev

HP kW		Pole		Fromo	Valtara	Hz	Phase	
10	7.5	4			Voltage 575	60	3	FL Amps 10.6
Enclosure	IP			Duty	NEMA Nom. Eff.	NEMA	kVA Code	Ambient
TEFC	56	F	1.15	CONT	91.7	Design B		(° C) 40 C
TEFC	56	F	1.15	CONT	91.7	В		40 C
oad	HP	kW	Ampe	eres	Efficienc	y (%)	Power Fa	actor (%)
ull Load	10.00	7.5	10.6		91.9		77.3	
Load	7.50	5.6	8.		91.0		71.9	
₂ Load	5.00	3.7	6.		88.5		61.9	
Load	2.50	1.9	4.	6	82.2		49.4	
o Load			5. [:] 64				5. 45	
ocked Rotor				<u> </u>				
	_	1	Torque					Rotor wk
Full Lo		Locked			ll Up		ak Down	Inertia
(lb-ft 29.8		(% F 30	-		FLT) 25	(%	% FLT) 345	(lb-ft²) 1.33
Cold	Llat	Pressure			NDE			
Colu	Hot	dB(A) @ 1M	DE		NDE		(Ib	-
35 Bearings are the only re	15	-	DE 6308		NDE 6308C		. (lb 21	-
35	15 commended spar	e part(s). Face Footed						-
35 Bearings are the only re lotor Options: Product Family:EQF Nounting:C-Face Fo	15 commended spar	e part(s). Face Footed						-
35 Bearings are the only re lotor Options: roduct Family:EQF Aounting:C-Face Fo	15 commended spar	e part(s). Face Footed						-
35 Bearings are the only re lotor Options: roduct Family:EQF Aounting:C-Face Fo Mounting:C-Face Fo ustomer ustomer PO ales Order	15 commended spar	e part(s). Face Footed						-
35 Bearings are the only re lotor Options: roduct Family:EQF Mounting:C-Face Fo Mounting:C-Face Fo Mounting:	15 commended spar	e part(s). Face Footed						-
35 otor Options: roduct Family:EQF founting:C-Face For ustomer ustomer PO ales Order roject # ag:	15 ecommended spar	e part(s). Face Footed shaft	6308	3C3	6308C			-
35 every of the only re- otor Options: Product Family:EQF Nounting:C-Face For Nounting:C-Face For Nounting	15 commended spar	e part(s). Face Footed shaft	6308	RPORATION · H	6308C	CAS U.S.A.	21	
35 Bearings are the only re Iotor Options: Product Family:EQF	15 commended spar P Global 841 Cl boted,Shaft:T S	e part(s). Face Footed shaft	6308	3C3	6308C	23 23 24 24 24 25 24 25 24 25 24 25 26 26 26 26 26 26 26 26 26 26 26 26 26		-



HP

10

Enclosure

TEFC

Locked Rotor

Amps

64

	Issued Date Issued By		6/20/2025 dschoeck		Transmit #		
					Issued Rev		
		UE/CURREN					
Pole	FL RPM	Frame	Voltage	Hz	Phase	FL Amps	
4 Ins. Class	1765 S.F.	215TC Duty	575 NEMA Nom. Eff.	60 NEMA Design	3 kVA Code	10.6 Ambient (°C)	
F	1.15	CONT	91.7	B		40 C	
			Torque				
Full Load	Locked		Pull U	р		Break Down	
(lb-ft) 29.8	(% 30		(%) 225		(%) 345		
20.0	50	~	220			~	
						50	
	•	-			Λ	50 80	
	•				6	80	
					6	⁸⁰ Current (%	
					6	80	

					\sim	
(%) anbjogram 160						⁵¹⁰ Current (%)
80						170
0	0 20		0 nchronous Spee		I \$0	100
Torq	ue <mark>Current</mark>					
Customer				wk ² Load Inertia	a (lb-ft²)	-
Sustomer PO					ad Type	-
ales Order					age (%)	100
Project #				Acce	el. Time	-
Гаg:						
Il characteristics are ave	erage expected values.					
All characteristics are ave		A INTERNATIONAL	CORPORATION ·	HOUSTON, TEXAS U	J.S.A.	
All characteristics are ave		A INTERNATIONAL	CORPORATION · Doc. Written By Doc. Approved By	D. Suarez		:#/Rev MPCF-1121/0

400

320

Model: 0104XDSC42A-P

kW

7.5

IP

56

Rotor wk²


Inertia


(lb-ft²)

1.33

3SVD

Motor Connection Diagram 3 Leads - Delta Connection





Switch L1 and L2 to reverse rotation

Each lead may consist of more than one cable. If multiple cables represent a single lead, each one of them will be labeled with the appropriate lead number.

				Issued Date:	6/20/20)25	Transmit #:	
TOSH	IIBA			Issued By:	dschoeck		Issued Rev:	
	novation >>>	•	SPAR	E PARTS LIST	[*			
Model	: 0104XDSC42	A-P						
HP	kW	Pole	FL RPM	Frame	Voltage	Hz	Phase	FL Amps
10	7.5	4	1765	215TC	575	60	3	10.6
Enclosure	IP	Ins. Class	S.F.	Duty	NEMA Nom. Eff.	NEMA Design	kVA Code	Ambient (°C)
TEFC	56	F	1.15	CONT	91.7	В		40 C
	•	•		•		•		
earings DE	6308C3 / 40E	3C03J3OX						
earings NDE	6308C3 / 40E	3C03J3OX						

*Bearings are the only recommended spare part(s).

Other than the grease used for regreasable bearings and the oil used for oil-lubricated bearings, Toshiba advises that there are no "use" parts. The only insurance spares that Toshiba suggests for these squirrel-cage induction motors are industry-standard and commercially available off-the-shelf bearings as noted above.

Motor components such as terminal boxes, fan covers and other machined parts are available on special request. In these cases, please advise our order entry department of the model and serial numbers found on the motor nameplate and a description of the needed components. With this information they will be able to furnish the current part number, price and availability.

Note: Our internal part numbers are subject to change without notice and are not published.

Customer										
Customer PO										
Sales Order										
Project #										
_	Tag:									
All characteristics are av	All characteristics are average expected values.									
TOSHIBA INTERNATIONAL CORPORATION · HOUSTON, TEXAS U.S.A.										
Engineering	bmammen	Doc. Written By	D. Suarez	Doc.#/Rev	MPCF-1125 / 0					
Engr. Date	5/5/2025	Doc. Approved By	M. Campbell	Doc. Issued	6/8/2011					