

Safe Stall Time(s)		Sound	Bearin	Approx. Motor Weight	
Cold	Hot	Pressure dB(A) @ 1M	Dealin	Approx. Motor weight	
Cold			DE	NDE	(lbs)
35	15	-	6308C3	6308C3	187

\*Bearings are the only recommended spare part(s).

Motor Options:

Product Family:EQP Global 841 Mounting:C-Face Round,Shaft:T Shaft

Engr. Date

Customer
Customer PO
Sales Order
Project #
Tag:

5/5/2025

All characteristics are average expected values.

 TOSHIBA INTERNATIONAL CORPORATION · HOUSTON, TEXAS U.S.A.

 Engineering
 bmammen
 Doc. Written By
 D. Suarez
 Doc.# / Rev
 MPCF-1119 / 0

Doc. Approved By

M. Campbell

Doc. Issued

6/8/2011



HP

7.50

Enclosure

TEFC

Locked Rotor

Amps

50

Model: Y754XDSC44A-P

kW

5.5

IP

56

Rotor wk<sup>2</sup>

Inertia

(lb-ft<sup>2</sup>)

1.15

Pole

4

Ins. Class

F

Full Load

(lb-ft)


22.3


		Issued Date 6/20/2025			Transmit #	
		Issued By	Issued By dschoeck			
SF	PEED TORQ	UE/CURREN	T CURVE			
	FL RPM	Frame	Voltage	Hz	Phase	FL Amps
	1770	213TC	575	60	3	8.2
	S.F.	Duty	NEMA Nom. Eff.	NEMA Design	kVA Code	Ambient (°C)
	1.15	CONT	91.7	В		40 C
			Torque			
Τ	Locked	Rotor	Pull Up	)	Break	Down
	(%	6)	(%)		(%	6)
	26	30	195		31	15
	De	sign Value	es			50
					Λ	



3SVD

## Motor Connection Diagram 3 Leads - Delta Connection





Switch L1 and L2 to reverse rotation

Each lead may consist of more than one cable. If multiple cables represent a single lead, each one of them will be labeled with the appropriate lead number.

тоси	DA			Issued Date:         6/20/2025           Issued By:         dschoeck		-	Transmit #: Issued Rev:	
TOSH Leading Inno		•	SPAR	E PARTS LIS	<u> </u>		135000 1107.	
	Y754XDSC44							
Model: HP	Y754XDSC44	A-P Pole	FL RPM	Frame	Voltage	Hz	Phase	FL Amps
			<b>FL RPM</b> 1770	Frame 213TC	Voltage 575	<b>Hz</b> 60	Phase 3	FL Amps 8.2
HP	kW	Pole			•			

HP	kW	Pole	FL RPM	Frame	Voltage	Hz	Phase	FL Amps		
7.50	5.5	4	1770	213TC	575	60	3	8.2		
Enclosure	IP	Ins. Class	S.F.	Duty	NEMA Nom. Eff.	NEMA Design	kVA Code	Ambient (°C)		
TEFC	56	F	1.15	CONT	91.7	В		40 C		
Bearings DE	6308C3 / 40B	6308C3 / 40BC03J3OX								
Bearings NDE	6308C3 / 40B	6308C3 / 40BC03J3OX								

\*Bearings are the only recommended spare part(s).

Other than the grease used for regreasable bearings and the oil used for oil-lubricated bearings, Toshiba advises that there are no "use" parts. The only insurance spares that Toshiba suggests for these squirrel-cage induction motors are industry-standard and commercially available off-the-shelf bearings as noted above.

Motor components such as terminal boxes, fan covers and other machined parts are available on special request. In these cases, please advise our order entry department of the model and serial numbers found on the motor nameplate and a description of the needed components. With this information they will be able to furnish the current part number, price and availability.

Note: Our internal part numbers are subject to change without notice and are not published.

Customer								
Customer PO								
Sales Order								
Project #								
Tag:								
All characteristics are average expected values.								
TOSHIBA INTERNATIONAL CORPORATION · HOUSTON, TEXAS U.S.A.								
Engineering	bmammen	Doc. Written By	D. Suarez	Doc.#/Rev	MPCF-1125 / 0			
Engr. Date	5/5/2025	Doc. Approved By	M. Campbell	Doc. Issued	6/8/2011			