

8.4

6.8

4.6

5.7

ocked Rotor 63 39					
Torque					
Full Load	Locked Rotor	Pull Up	Break Down	Inertia	
(lb-ft)	(% FLT)	(% FLT)	(% FLT)	(lb-ft <sup>2</sup> )	
	260	195	315	1.15	

90.5

87.5

80.6

68.8

58.4

46.9

5.0

Safe Stall	Time(s)	Sound	Bearin	ac*	Approx. Motor Weight	
Cold	Hot	Pressure	Bearings*		Approx. motor weight	
Colu	пог	dB(A) @ 1M	DE	NDE	(lbs)	
35	15	-	6308ZZC3	6308ZZC3	194	

\*Bearings are the only recommended spare part(s).

Motor Options:

3/4 Load

1⁄₂ Load

1/4 Load

No Load

Product Family:EQP Global 840 CFace Footed Mounting:C-Face Footed,Shaft:T Shaft

5.62

3.75

1.87

4.2

2.8

1.4

Customer Customer PO Sales Order Project # Tag:

All characteristics are average expected values. TOSHIBA INTERNATIONAL CORPORATION · HOUSTON, TEXAS U.S.A. Engineering bmammen Doc. Written By D. Suarez Doc.# / Rev MPCF-1119/0

Doc. Approved By

M. Campbell

Doc. Issued

6/8/2011

Engr. Date

5/5/2025



HP

7.50

Enclosure TEFC

Locked Rotor

Amps

63

350

280

		Issued Date	6/20/202	25	Transmit #	
		Issued By	dschoed	ж	Issued Rev	
S	PEED TORQ	UE/CURREN	IT CURVE			
	FL RPM	Frame	Voltage	Hz	Phase	FL Amps
	1770	213TC	460	60	3	10.3
;	S.F.	Duty	NEMA Nom. Eff.	NEMA Design	kVA Code	Ambient (°C)
	1.15	CONT	91.7	В		40 C
			Torque			
	Locked		Pull Up	)	Break Down	
	(%)		(%)		(%)	
	26	0	195		315	
	Des	sign Valu	es		<b>^</b>	00
					6	40
					<b>```````````````````````````````````</b>	80 <u>2</u>
	-		-		<b>~ 1</b>	=

Model: Y754XSSB42A-P

kW

5.5

IP

55

Rotor wk<sup>2</sup>

Inertia

(lb-ft<sup>2</sup>)

1.15

Pole

4

Ins. Class

F

Full Load


(lb-ft)


22.3

210				480	
(%) 140					
n					
E I				•	
⊢ <sub>140</sub>				320 🗳	
				1	
70				160	
				4	
				1	
٥					
0	20		60 80	100	
		Synchronous Spee	d (%)		
Torque	Current				
ustomer			wk <sup>2</sup> Load Inertia (lb-ft <sup>2</sup> )	-	
ustomer PO		1	Load Type	-	
ales Order			Voltage (%)	100	
roject #			Accel. Time	-	
ag:					
Il characteristics are average					
1	TOSHIBA INTE bmammen	RNATIONAL CORPORATION ·			
Engineering	5/5/2025	Doc. Written By	D. Suarez		-1121/0
Engr. Date	5/5/2025	Doc. Approved By	M. Campbell	Doc. Issued 6/	8/2011

3SVD

## Motor Connection Diagram 3 Leads - Delta Connection





Switch L1 and L2 to reverse rotation

Each lead may consist of more than one cable. If multiple cables represent a single lead, each one of them will be labeled with the appropriate lead number.

## TOSHIBA Leading Innovation >>>

21510				
213TC	460	60	3	10.3
Frame	Voltage	Hz	Phase	FL Amps
	Frame	¥	Frame Voltage Hz	Frame Voltage Hz Phase

Model: Y754XSSB42A-P

		1 010		Traine	Voltage	112	1 11430		
7.50	5.5	4	1770	213TC	460	60	3	10.3	
Enclosure	IP	Ins. Class	S.F.	Duty	NEMA Nom. Eff.	NEMA Design	kVA Code	Ambient (°C)	
TEFC	55	F	1.15	CONT	91.7	В		40 C	
Bearings DE	6308ZZC3 / 4	0BC03JPP3OX							
Bearings NDE	6308ZZC3 / 40BC03JPP3OX								

\*Bearings are the only recommended spare part(s).

Other than the grease used for regreasable bearings and the oil used for oil-lubricated bearings, Toshiba advises that there are no "use" parts. The only insurance spares that Toshiba suggests for these squirrel-cage induction motors are industry-standard and commercially available off-the-shelf bearings as noted above.

Motor components such as terminal boxes, fan covers and other machined parts are available on special request. In these cases, please advise our order entry department of the model and serial numbers found on the motor nameplate and a description of the needed components. With this information they will be able to furnish the current part number, price and availability.

Note: Our internal part numbers are subject to change without notice and are not published.

Customer							
Customer PO							
Sales Order							
Project #							
Tag:							
All characteristics are av							
All characteristics are av	• 1						
TOSHIBA INTERNATIONAL CORPORATION · HOUSTON, TEXAS U.S.A.							
Engineering	bmammen	Doc. Written By	D. Suarez	Doc.# / Rev	MPCF-1125 / 0		
Engr. Date	5/5/2025	Doc. Approved By	M. Campbell	Doc. Issued	6/8/2011		